



900 SERIES

MIXER/ AMPLIFIERS:

A-903MK2

A-906MK2

A-912MK2

THE TOA 900 SERIES are widely recognized as the industry standard in installed sound system amplification. When reliability and performance are critical – such as in paging and music distribution for airport, hospital, and industrial sound systems – you can count on the TOA 900 Series to perform consistently, day-in and day-out.

The **A-903MK2** (30 W), **A-906MK2** (60 W) and **A-912MK2** (120 W) **Modular Mixer/Amplifiers** are engineered for high performance with wide frequency response, very low noise and distortion, and excellent output regulation. Eight module slots allow you to easily configure custom configurations using TOA plug-in modules with an extensive array of features and connector types. You can increase the input capacity by connecting a second mixer or mixer/amplifier to the rear-panel Bridge In/Out jack. Outputs include transformer-isolated 25 V, 70 V and 8 ohm (A-903MK2: 4 ohm) plus a direct low-impedance mode if non-transformer operation is required.

Multiple paging priorities are easily configured using optional mute-type modules activated by external switch-closure or mute-send modules. Pre-Out/Power-In jacks allow connection of external signal processing between the mixer and amplifier sections. Other features include protection circuitry, auxiliary output, bass/treble controls and remote master volume terminals.

The 900 Series Mixer/Amplifiers are UL and cUL Listed and carry a five year warranty.



HIGHLIGHTS

- **Modular Eight Channel Mixer/ Amplifiers** for paging, background/ foreground music distribution and music/messaging-on-hold.
- **Proven TOA Quality and Reliability**
- **Engineered for High Performance** with wide frequency response, very low noise and distortion, and excellent output regulation.
- **Three Models:** **A-903MK2** (30 W), **A-906MK2** (60 W), **A-912MK2** (120 W)
- **Eight Module Slots** accept any combination of TOA plug-in modules for custom system configurations.
- **25 V, 70 V and 8 Ohm Transformer-Isolated Speaker Outputs** with screw terminal connector and protective cover plate (A-903MK2: 4 ohm).
- **Direct Low-Impedance Output Mode** bypasses output transformer.
- **Dual Mute Bus** permits multiple levels of paging priority using optional mute-type modules.
- **External Mute Terminals** for activating mute function with external switch-closure.
- **Remote Master Volume Terminals** for control with an external 10k ohm linear-taper potentiometer.
- **Individual Channel and Master Volume Controls.**
- **Bass/Treble Tone Controls** with tone defeat switch.
- **Low Cut Switch** to limit low frequency response.
- **Auxiliary Output** for connecting an external mixer or recording device.
- **Insert Jacks** for connecting external signal processing.
- **Bridging Input/Output** for input expansion or recording device.
- **Normal, Clip, Power, Protect, and Signal Indicators** provide unit status.
- **Rear Panel AC Convenience Outlet** for powering external equipment
- **Turn-On Delay** disconnects output during power-up.
- **Over-current and Thermal Protection Circuitry** prevents potential damage from overload, short-circuit and overheating.
- **Volume Control Security Knobs Included (4)**
- **Optional Rack-Mount Kits**
- **UL / cUL Listed**
- **Five Year Warranty**

OPTIONAL ACCESSORIES

Plug-in Modules (see individual module specifications)

MB-25B Rack-mount Kit (2 RU)

PF-511 Perforated Rack Panel (2 RU)

YA-920 Volume Control Security Knob

900 Series Module Guide available from <http://www.toaelectronics.com>

SPECIFICATIONS

900 SERIES
MIXER/AMPLIFIERS

Tel: 800-733-7088
Fax: 800-733-9766
www.toaelectronics.com



Type	8-channel modular mixer/amplifier
Output Power	A-903MK2: 30 W RMS; A-906MK2: 60 W RMS A-912MK2: 120 W RMS
Power Bandwidth	(D) 20 - 20k Hz, 0.5% THD; (T) 50 - 20k Hz, 0.5% THD
Frequency Response	(D) 20 - 20k Hz, ± 1 dB; (T) 20 - 15k Hz, ± 1 dB (T) 20 - 20k Hz, +1 dB / -3 dB
Total Harmonic Distortion	0.02% at 1k Hz, rated output
Inputs	8 input ports: every port accepts any input module 1 Bridging Input/Output
Input Sensitivity & Impedance	Please refer to 900 Series module specifications. Bridging Input/Output: 100 mV / 3.3k Ω
Pre-amp. Out/ Power Amp. In	1 V, 600 Ω / 1 V, 10k Ω
Outputs <small>(T)=Transformer (D)=Direct</small>	Main (T): 8 Ω , 25 V & 70 V, balanced Main (D): 4 Ω , unbalanced Aux: 1 V, 10k Ω
Output Regulation <small>(1k Hz)</small>	(D): Less than 0.5 dB, no load to full load (T): Less than 1.0 dB, no load to full load
Dynamic Range <small>(Band Pass: 20 - 20k Hz, with Tone Controls centered)</small>	Master volume set to min.: 90 dB Master volume set to max.: 77 dB Power amplifier only: 105 dB
Tone Controls	Bass: ± 10 dB at 100 Hz; Treble: ± 10 dB at 10k Hz
Indicators	Normal, Peak, Power, Protect, and Signal LEDs
Protection	Self-protection, with internal AC fuse
Power Consumption	A-903MK2: 60 W; A-906MK2: 100 W; A-912MK2: 180 W
Temperature Range	12° F to 140° F (-10° C to +60° C)
Color	Black
Dimensions (W x H x D)	A-903MK2: 16.5" x 3.9" x 12.5" (420 x 99.1 x 318 mm) A-906/912MK2: 16.5" x 3.9" x 14.1" (420 x 99.1 x 358 mm)
Weight (without modules)	A-903MK2: 17.2 lbs (7.8 kg); A-906MK2: 21.2 lbs (9.6 kg) A-912MK2: 25.1 lbs (11.4 kg)
Other Features	Output connects approx. 5 seconds after switching power on.

APPLICATIONS

A/V Rentals
Airports
Audio/Visual
Auditoriums / Theatres
Banks
Bars / Lounges / Nightclubs
Boardrooms
Business Music
Conference Facilities
Convenience Stores
Educational Facilities
Fitness Clubs / Gymnasiums
Hotels / Hospitality
Houses of Worship
Industrial / Warehouses
Museums
Music Distribution
Offices
Public Address
Restaurants
Retail Stores
Theme Parks
Training Rooms

Visit www.toaelectronics.com to download:

900 Series Architect and Engineering Specifications
900 Series Installation Manual
900 Series CAD Files
900 Series Module Guide



900 SERIES
MIXER/AMPLIFIERS

Tel: 800-733-7088
Fax: 800-733-9766
www.toaelectronics.com

MODULE SELECTION




Model	Type	Description
M-01F	MIC	Microphone Input Module, Balanced, 200 Ω , Lo/Hi-Cut Filters, Female XLR
M-01M	MIC	Same as M-01F with Male XLR
M-01P	MIC	Same as M-01F with Phone Jack
M-01S	MIC	Same as M-01F with Screw Terminals
M-03P	MIC	Microphone Input Module, HiZ, Unbalanced, 50k Ω , Lo/Hi-Cut Filters, Phone Jack
M-11S	MIC	Microphone Input Module, Balanced, 200 Ω , Lo/Hi-Cut Filters, Mute-Receive, Screw Terminals
M-21S	MIC	Microphone Input Module, Balanced, 200 Ω , Lo/Hi-Cut Filters, Remote Vol. Control, Screw Terminals
M-41S	MIC	Microphone Input Module, Balanced, 200 Ω , Lo/Hi-Cut Filters, Mute-Send, Removable Terminal Block
M-51F	MIC	Microphone Input Module, Balanced, 200 Ω , Lo-Cut Filter, Voice Gate, Female XLR
M-51S	MIC	Same as M-51F with Screw Terminals
M-61F	MIC	Microphone Input Module, Balanced, 200 Ω , Lo/Hi-Cut Filters, Compressor, Female XLR
M-61S	MIC	Same as M-61F with Screw Terminals
B-01F	LINE	Balanced Line Input Module, 10k Ω Transformer, Female XLR
B-01S	LINE	Balanced Line Input Module, 10k Ω Transformer, Screw Terminals
B-11S	LINE	Balanced Line Input Module, 10k Ω Transformer, Mute-Receive, Screw Terminals
B-21S	LINE	Balanced Line Input Module, 10k Ω Transformer, Remote Volume Control, Screw Terminals
B-41S	LINE	Balanced Line Input Module, 10k Ω Transformer, Mute-Send, Removable Terminal Block
L-01F	LINE	Line Matching Input Module, 600 Ω Transformer, Balanced, Female XLR
L-01S	LINE	Same as L-01F with Screw Terminals
L-11S	LINE	Line Matching Input Module, 600 Ω Transformer, Balanced, Mute-Receive, Screw Terminals
L-41S	LINE	Line Matching Input Module, 600 Ω Transformer, Balanced, Mute-Send, Screw Terminals
U-01F	LINE	Line Input Module, Unbalanced, 220k Ω , Female XLR
U-01P	LINE	Same as U-01F with Phone Jack
U-01R	LINE	Same as U-01F with RCA Jack
U-01S	LINE	Same as U-01F with Screw Terminals
U-03R	LINE	Stereo Line Input Module, Lo/Hi-Cut Filters, Stereo Summing Dual RCA Jacks
U-03S	LINE	Line Input Module, Lo/Hi-Cut Filters, Screw Terminals
U-11R	LINE	Line Input Module, Unbalanced, 220k Ω , Mute-Receive, RCA Jack
U-11S	LINE	Line Input Module, Unbalanced, 220k Ω , Mute-Receive, Screw Terminals
U-12S	LINE	Line Input Module, Unbalanced, 220k Ω , Variable Mute-Receive Depth, Screw Terminals
U-13R	LINE	Same as U-03R with Mute-Receive
U-13S	LINE	Same as U-03S with Mute-Receive
U-21S	LINE	Line Input Module, Unbalanced, 220k Ω , Remote Volume Control, Screw Terminals
U-43R	LINE	Same as U-03R with Mute-Send
U-43S	LINE	Same as U-03S with Mute-Send
U-61S	LINE	Line Input Module, Unbalanced, 220k Ω , Compressor, Screw Terminals
E-03R	SPECIAL FUNCTION	900 Series Processor Module for F-121C/CM Speakers, Dual RCA Jacks
E-04R	SPECIAL FUNCTION	900 Series Processor Module for H-1 Speakers, Dual RCA Jacks
E-05R	SPECIAL FUNCTION	900 Series Processor Module for H-2/H-2WP Speakers, Dual RCA Jacks
E-06R	SPECIAL FUNCTION	900 Series Processor Module for H-3/H-3WP Speakers, Dual RCA Jacks
E-07S	SPECIAL FUNCTION	900 Series Low Pass Filter Output Module for FB-100 and HB-1, Removable Terminal Block
S-01S	SPECIAL FUNCTION	Signal Generator Module, 1 kHz Sine Wave, Screw Terminals
S-02S	SPECIAL FUNCTION	Signal Generator Module, Buzzer/Yelp, Screw Terminals
S-04S	SPECIAL FUNCTION	Signal Generator Module, 8 Selectable Tones, Screw Terminals
T-01S	SPECIAL FUNCTION	Line Output Module, Balanced, 600 Ω , Screw Terminals
T-02S	SPECIAL FUNCTION	Line Input Module for Music-on-Hold, Unbalanced, 220k Ω Input, 600 Ω Balanced Output, Screw Terminals
T-12S	SPECIAL FUNCTION	Same as T-02S with Input Mute-Receive



TOA ELECTRONICS, INC.
 601 GATEWAY BLVD., SUITE 300
 SOUTH SAN FRANCISCO, CA 94080
 TEL: 800-733-7088
 FAX: 800-733-9766
www.toaelectronics.com

900 SERIES MIXER/ AMPLIFIERS



Female XLR Male XLR 1/4" Phone Jack RCA Jack Dual RCA Jacks 3 Screw Terminals 5 Screw Terminals Removable Terminal Block

900 SERIES MODULE CHART

		Female XLR	Male XLR	1/4" Phone Jack	RCA Jack	Dual RCA Jacks	3 Screw Terminals	5 Screw Terminals	Removable Terminal Block
Microphone Input Modules	Standard with high/low cut filters	M-01F	M-01M	M-01P			M-01S		
	Mute-Receive with high/low cut filters						M-11S		
	Mute-Send with high/low cut filters								M-41S
	Voice Gate with low cut filters	M-51F					M-51S		
	Compressor with high/low cut filters	M-61F					M-61S		
	Remote Volume Control with high/low filters							M-21S	
	For high-Z mic. only w/ high/low cut filters			M-03P					
Line Input Modules*	Standard, no special features	L-01F B-01F U-01F		U-01P	U-01R		L-01S B-01S U-01S		
	Standard with high/low cut filters					U-03R			U-03S
	Mute-Receive				U-11R		L-11S B-11S U-11S		
	Mute-Receive with high/low cut filters					U-13R			U-13S
	Mute-Receive with variable mute depth						U-12S		
	Mute-Send						L-41S		B-41S
	Mute-Send with high/low cut filters					U-43R			U-43S
	Remote Volume Control							B-21S U-21S	
	Compressor						U-61S		
Special Function Modules	Line output						T-01S		
	Line input with Music-On-Hold (MOH) output							T-02S	
	Line input w/ MOH & input Mute-Receive							T-12S	
	1 kHz Sine Wave test tone						S-01S		
	Buzzer/Yelp signal tone						S-02S		
	Switch-selectable tone						S-04S		
	Equalizer for F-121C/CM Speakers					E-03R			
	Equalizer for H-1 Speakers					E-04R			
	Equalizer for H-2/H-2WP Speakers					E-05R			
	Equalizer for H-3/H-3WP Speakers					E-06R			
Low Pass Filter for FB-100/HB-1 Speakers								E-07S	

*For Line Input Modules: Use "B" modules w/ transformer isolation for balanced/unbalanced sources. Use "L" modules only for 600 ohm impedance matching. Use "U" for unbalanced sources w/ short cables (≤ 15 feet).

MUTING MODULES

The two types of muting modules, MUTE-RECEIVE and MUTE-SEND, have mute function circuitry that connects to two common "MUTE" buses, and one common "GROUND" bus when installed in an A-900MK2 mixer/amplifier or M-900MK2 mixer/pre-amplifier. A "BUS" is simply an internal wire that connects from module-slot to module-slot. You can access these buses via rear-panel screw terminals, labeled, "MUTE 1", "MUTE 2" and "GND". Mute-type modules connect to both mute buses "out-of-the-box". You can disconnect the module's mute function circuitry from each mute bus by cutting jumper wires on the modules. This allows you to configure systems with multiple levels of priority.

MUTE-RECEIVE modules respond to mute bus activation in either of two ways: 1) Switch Activation: Connecting a switch closure between the "MUTE" (1 or 2)" and "GND" screw terminals on the rear of the mixer/amplifier activates the mute function circuitry of MUTE-RECEIVE modules connected to the same bus. This is also referred to as "manual muting". 2) Auto-Mute: When input signal level to a MUTE-SEND module exceeds a user-adjustable threshold, the module's mute function circuitry activates the mute function circuitry of all MUTE-RECEIVE modules connected to the same bus. This is also referred to as "signal-activated muting".