

# Orchestra<sup>2</sup> - Ref. ORC50

NEW

Powerful Intuitive and Ergonomic Remote Controller for Rental and Staging/  
Multi-venues/Integration



## Special tips

The Orchestra<sup>2</sup> can be controlled by an external controller from CRESTRON®, AMX® or any other major control system.

## Orchestra<sup>2</sup> at a glance

- ▶ User-friendly and powerful Remote Controller
- ▶ Controls simultaneously up to 6 screens in single or multiple display configuration
- ▶ Can store up to 64 presets per screen selection
- ▶ Controls a large number of Analog Way's Seamless Switchers
- ▶ Off-Line Programming
- ▶ Snap Function
- ▶ Equipped with a USB port, the complete configuration of the event can be saved for future use

## To control the following Seamless Switchers

- |                           |                                    |
|---------------------------|------------------------------------|
| ▶ DVX8044: Di-VentiX II   | ▶ STE100: Smart Edge               |
| ▶ EKS500: Eikos           | ▶ EKS550: Eikos <sup>2</sup>       |
| ▶ EKS400: Eikos LE        | ▶ SPX450: Saphyr                   |
| ▶ SMX200: Smart MatriX    | ▶ PLS350: Pulse <sup>2</sup>       |
| ▶ SMX100: Smart MatriX LE | ▶ PLS350: Pulse <sup>2</sup> -3G   |
| ▶ PLS300: Pulse           | ▶ QVU150: QuickVu                  |
| ▶ PLS200: Pulse LE        | ▶ QVU150: QuickVu-3G               |
| ▶ SQD200: Smart Quad      | ▶ QMX150: QuickMatriX              |
| ▶ STE200: Smart Edge FX   | ▶ SMX250: SmartMatriX <sup>2</sup> |

## Technical Specifications

- ▶ **User Controls**
  - TFT touch screen, 7" (18 cm)
  - Buttons for direct access to inputs
  - Buttons for direct access to effects
  - User preset buttons
  - Take, Freeze, Main and Preview selection
  - T-Bar for smooth manually controlled transitions
  - Joystick for easy and fast set up of image or effect parameters
- ▶ **Connectors**
  - RJ45 for TCP/IP Ethernet connection
  - USB port
  - Auxiliary VGA
  - BNC for desk light

## External Programming

All Presets can be prepared on the Orchestra<sup>2</sup> and recalled by Control Systems. Templates can be selected and filled by chosen source. Simple and affordable, the Orchestra<sup>2</sup> saves time and money by programming complicated presets which can be recalled by a third party controller and later changed without reprogramming the third-party controller.

### Dimensions:

- ▶ Compatible 19", 6U
- ▶ D 17.7" x W 17.7" x H 7"
- ▶ D 450 mm x W 450 mm x H 180 mm

### Weight:

- ▶ 9 kg
- ▶ 20 lbs

### Power Supply:

Internal, universal, automatic 100-250 VAC; 50/60 Hz (100W) (UL, CSA, GS, CE) On/Off power switch

### Supplied with:

- ▶ 1 x Power Supply Cord
- ▶ 1 x Rack mount plate and screws
- ▶ 2 x Adjustable feet
- ▶ 1 x User Manual (PDF version)\*
- ▶ 1 x Quick Start Guide\*

### Warranty:

3-year warranty on parts and labor back to factory.



\* The Quick Start Guide and the User Manual are also available on [www.analogway.com](http://www.analogway.com)

Specifications subject to change without prior notice

All technical specifications are available on our website

Follow us

