



BNC & HD-BNC Connector to Coax Cable, Crimp Tool & Stripping Tool Cross Reference Chart

Coax Color Code Legend

| | |
|------------------|------------------|
| Belden 1855/4855 | Belden 1505/4505 |
| Belden 1694/4694 | Belden 4794 |



| Kings 12G | 2065-11-9 | 2065-10-9 | 2065-2-9 | KNG-HHD1855A |
|-----------------------|----------------------|---------------|----------------------|----------------|
| BNC Type | 3-Piece Plug | 3-Piece Plug | 3-Piece Plug | 3-Piece HD-BNC |
| Coax Type | Mini-RG59 | RG6 | RG59 | Mini-RG59 |
| Belden | 1855A | 1694A / 1695A | 1505A | 1855A |
| Coax | 4855R / 4855P | 4694R / 4694P | 4505R | 4855R / 4855P |
| Gepeco Coax | VDM230 | VSD2001 | VPM2000 | VDM230 |
| West Penn | N/A | WP-6350 | WP-819 | N/A |
| Canare Coax | N/A | L-5CFB | L-4CFB | N/A |
| Kings Crimp Die | KTH-2025 | KTH-2325 | KTH-2261 | KTH-2025 |
| Kings Crimp Tool | KTH1000 | KTH1000 | KTH1000 | KTH1000 |
| Paladin Crimper w/Die | PAL-1366 PAL-1389 | - | PAL-1366 PAL-1389 | PAL-1366 |
| Paladin Stripper | PAL-1247 | PAL-1247 | PAL-1247 | PAL-1247 |
| Canare Stripper | TS100U | TS100U | TS100U | TS100U |



| Canare 3G BNC | BCP-B26 | BCP-B25HD | BCP-B25HW | BCP-B3F | BCP-B31F |
|-------------------------|---------------|---------------------|--------------|--------------|--------------------|
| Model | BCP-B26 | BCP-B25HD | BCP-B25HW | BCP-B3F | BCP-B31F |
| BNC Type | 3-Piece Plug | 3-Piece Plug | 3-Piece Plug | 3-Piece Plug | 3-Piece Plug |
| Canare Coax | - | L-2.5CHD, L-2.5CHLT | L-2.5CHWS | L-3CFB | L-3CFW |
| Fits Belden Coax | 1855A / 1855P | 4855R | - | - | - |
| Canare Crimp Tool Frame | TC1 | TC1 | TC1 | TC1 | TC1 |
| Canare Crimp Die | TC-D-35C | TC-D-35C | TC-D-35C | TC-D-35C | TC-D-4C, TC-D-451C |
| Canare Stripper | TS100U | TS100U | TS100U | TS100U | TS100U |
| Paladin Crimper w/Die | PAL-1366 | PAL-1366 | PAL-1366 | - | - |
| Paladin Stripper | PAL-1248 | PAL-1248 | PAL-1248 | - | - |

| Canare 3G BNC | BCP-B45HW | BCP-B4F | BCP-B51F | CNR-BCP-B53 | BCP-B5F |
|-------------------------|--------------|--------------|--------------|----------------------|----------------|
| Model | BCP-B45HW | BCP-B4F | BCP-B51F | CNR-BCP-B53 | BCP-B5F |
| BNC Type | 3-Piece Plug | 3-Piece Plug | 3-Piece Plug | 3-Piece Plug | 3-Piece Plug |
| Canare Coax | L-4.5CHWS | L-4CFB | L-5CFW | L-4.5CHD, L-4.5CHDPL | L-5CFB, V-5CFB |
| Fits Belden Coax | 1694F | - | - | 1694A / 4694R | - |
| Canare Crimp Tool Frame | TC1 | BL-BB3PHCT | TC1 | TC1 | TC1 |
| Canare Crimp Die | TC-D-35C | - | TC-D-5CF | TC-D-35C | TC-D-5CF |
| Canare Stripper | TS100U | TS100U | TS100U | TS100U | TS100U |
| Paladin Crimper w/Die | - | PAL-1366 | - | - | - |
| Paladin Stripper | PAL-1248 | PAL-1248 | - | PAL-1248 | PAL-1248 |

| Canare 12G BNC | BCP-D33UHD | BCP-D55UHD | BCP-D55UHW | BCP-D57 | BCP-D8UHD |
|-------------------------|--------------|--------------|--------------|--------------|-----------------|
| Model | BCP-D33UHD | BCP-D55UHD | BCP-D55UHW | BCP-D57 | BCP-D8UHD |
| BNC Type | 3-Piece Plug | 3-Piece Plug | 3-Piece Plug | 3-Piece Plug | 3-Piece Plug |
| Canare Coax | L-3.3CUHD | L-5.5CUHD | L-5.5CUHWS | - | L-8CUHD, L-8CHD |
| Belden Coax | - | - | - | 4794R | - |
| Canare Crimp Tool Frame | TC1 | TC1 | TC1 | TC1 | CAN-TC-2 |
| Canare Crimp Die | TC-D-35C | TCD-55UHD | TCD-57C | TCD-57C | TCD-8HD |
| Canare Stripper | TS100U | TS100U | TS100U | TS100U | TS100U |

| Canare 12G HD-BNC (Micro BNC) | HBCP-D25HD | HBCP-D25HW | HBCP-D33UHD | HBCP-D53 |
|-------------------------------|---------------------|------------|-------------|-----------------------|
| Model | HBCP-D25HD | HBCP-D25HW | HBCP-D33UHD | HBCP-D53 |
| Canare Coax | L-2.5CHD, L-2.5CHLT | L-2.5CHWS | L-3.3CUHD | L-4.5CHD, L-4.5CHD-PL |
| Belden Coax | 1855A | - | - | 1694A |
| Canare Crimp Tool Frame | TC1 | TC1 | TC1 | TC1 |
| Canare Crimp Die | TCD-D253F | TCD-D253F | TCD-D253F | TCD-D534F |
| Canare Stripper | TS100U | TS100U | TS100U | TS100U |

| Belden 12G BNC | 12G Mini-RG59 Coax (4855) | | 12G RG6 Coax (4694) | |
|-----------------------|---------------------------|----------------|---------------------|----------------|
| Model | 4855RBUHD3 | BL-4855RBUHD1 | BL-4694RBUHD3B50 | BL-4694RBUHD1 |
| BNC Type | 3-Piece Plug | Compression | 3-Piece Plug | Compression |
| Fits Belden Coax | 4855R 4855P | 4855R 4855P | 4694R 4694P | 4694R 4694P |
| Belden Crimp Tool | BL-BB3PHCT | ICM-CPLCRBC-B | BL-BB3PHCT | ICM-CPLCRBC-B |
| Paladin Crimper w/Die | PAL-1366 | - | - | - |
| Belden Stripping Tool | ICM-PSA596 | PS59-6-RGB | ICM-PSA596 | ICM-PSA596 |
| Paladin Stripper | PAL-1258 | - | PAL-1248 | - |
| Canare Stripper | - | - | TS100U | - |

| Belden 12G BNC | 12G RG59 Coax (4505) | | 12G Series 7 Coax (4794R) | |
|-----------------------|----------------------|------------------|------------------------------------|-----------------------------------|
| Model | BL-4505RBUHD3B50 | BL-4505RBUHD1B50 | BL-4794RBUHD3-S1 | BL-4794RBUHD1B50 |
| BNC Type | 3-Piece Plug | Compression | 3-Piece Plug | Compression |
| Fits Belden Coax | 4505R 4505P | 4505R 4505P | 4794R 4794P | 4794R 4794P |
| Belden Crimp Tool | BL-BB3PHCT | ICM-CPLCRBC-B | Kings KTH1000 with KTH-2260 Die | Kings KTH1000 with KTH-201 Die |
| Paladin Crimper w/Die | PAL-1366 | - | - | - |
| Belden Stripping Tool | | ICM-PSA596 | ICM-PSA596 | ICM-PSA596 |
| Paladin Stripper | PAL-1248 | - | PAL-1248 | - |
| Canare Stripper | TS100U | - | TS100U | - |

| Belden 12G Micro BNC (HD-BNC) | 12G Mini-RG59 Coax (4855) | 12G RG6 Coax (4694) | 12G RG59 Coax (4505) | 12G Series 7 Coax (4794R) |
|-------------------------------|----------------------------|----------------------------|----------------------------|----------------------------|
| Model | BL-4855RMBUHD350 | BL-4694RMBUHD350 | BL-4505RMBUHD350 | BL-4794RMBUHD350 |
| BNC Type | 3-Piece Micro BNC | 3-Piece Micro BNC | 3-Piece Micro BNC | 3-Piece Micro BNC |
| Fits Belden Coax | 4855R 4855P | 4694R 4694P | 4505R 4505P | 4794R 4794P |
| Belden Crimp Tool | BL-BB3PHCT BL-BB3PHCTD6 | BL-BB3PHCT BL-BB3PHCTD6 | BL-BB3PHCT BL-BB3PHCTD6 | BL-BB3PHCT BL-BB3PHCTD5 |
| Paladin Crimper w/Die | PAL-1366 | - | PAL-1366 | - |
| Belden Stripping Tool | ICM-PSA596 | ICM-PSA596 | ICM-PSA596 | ICM-PSA596 |
| Paladin Stripper | PAL-1248 | PAL-1248 | PAL-1248 | PAL-1248 |
| Canare Stripper | TS100U | TS100U | TS100U | TS100U |

| Belden 3G/6G BNC | 3G/6G Mini-RG59 Coax (1855) | | 3G/6G RG6 Coax (1694) | |
|-----------------------|-----------------------------|------------------|-------------------------|-------------------------|
| Model | BL-1855ABHD3-50P | BL-1855ABHD1-50P | BL-1694RBUHD3B50 | BL-1694RBUHD1 |
| BNC Type | 3-Piece Plug | Compression | 3-Piece Plug | Compression |
| Fits Belden Coax | 1855A 1855P | 1855A 1855P | 1694R 1694F 1695A | 1694R 1694F 1695A |
| Gepco Coax | VDM230 | VDM230 | VSD2001 | VSD2001 |
| West Penn | N/A | N/A | WP-6350 | WP-6350 |
| Canare Coax | N/A | N/A | L-5CFB | L-5CFB |
| Belden Crimp Tool | BL-BB3PHCT | ICM-CPLCRBC-B | BL-BB3PHCT | ICM-CPLCRBC-B |
| Paladin Crimper w/Die | PAL-1366 | - | - | - |
| Belden Stripping Tool | ICM-PSA596 | PS59-6-RGB | ICM-PSA596 | ICM-PSA596 |
| Paladin Stripper | PAL-1248 | - | PAL-1248 | - |
| Canare Stripper | TS100U | - | TS100U | - |

| Belden 3G/6G BNC | 3G/6G RG59 Coax (1505) | |
|-----------------------|-------------------------|-------------------------|
| Model | BL-1505RBUHD3B50 | BL-1505RBUHD1B50 |
| BNC Type | 3-Piece Plug | Compression |
| Fits Belden Coax | 1505A 1505F 1506A | 1505A 1505F 1506A |
| Gepco Coax | VPM2000 | VPM2000 |
| West Penn | WP-819 | WP-819 |
| Canare Coax | L-4CFB | L-4CFB |
| Belden Crimp Tool | BL-BB3PHCT | ICM-CPLCRBC-B |
| Paladin Crimper w/Die | PAL-1366 | - |
| Belden Stripping Tool | | ICM-PSA596 |
| Paladin Stripper | PAL-1248 | - |
| Canare Stripper | TS100U | - |

| Amphenol 12G BNC | Mini-RG59 Coax (4855 & 1855) | | | RG59 (4505R) |
|-----------------------|------------------------------|---------------------|------------------|------------------|
| Model | AMPH-0317053712G | AMPH-0317054412G | AMPH-0317053812G | AMPH-0317054612G |
| BNC Type | 3-Piece Plug | 2-Piece Right Angle | 3-Piece Jack | 3-Piece Plug |
| Belden | 4855R / 4855P | 4855R / 4855P | 4855R / 4855P | 4505R |
| Coax | 1855A / 1855P | 1855A / 1855P | 1855A / 1855P | 1505A |
| Canare Coax | - | - | - | - |
| Amphenol Crimp Tool | AMPH-47-10120 | AMPH-47-10120 | AMPH-47-10120 | AMPH-47-10110 |
| Paladin Crimper w/Die | PAL-1366 | PAL-1317 | PAL-1366 | PAL-1366 |
| Paladin Stripper | PAL-1247 | PAL-1247 | PAL-1247 | PAL-1247 |
| Canare Stripper | TS100U | TS100U | TS100U | TS100U |

| Amphenol 12G BNC | RG6 Coax (4694 & 1694) | | | 12G Series 7 Coax (4794R) | |
|-----------------------|------------------------|------------------|------------------|---------------------------|---------------------|
| Model | AMPH-0317054812G | AMPH-0317054712G | AMPH-0317055812G | AMPH-0317053912G | AMPH-0317054512G |
| BNC Type | 3-Piece Plug | 3-Piece Jack | 3-Piece Plug | 3-Piece Jack | 2-Piece Right Angle |
| Belden | 4694R | 4694R | 4694P | 4794R | 4794R |
| Coax | 1694A | 1694A | 1695A | 1794A | 1794A |
| Canare Coax | L-4.5CHWS | L-4.5CHWS | - | - | - |
| Amphenol Crimp Tool | AMPH-CTL14 | AMPH-CTL14 | AMPH-CTL14 | AMPH-47-10110 | AMPH-47-10110 |
| Paladin Crimper w/Die | - | - | - | PAL-2649 (die only) | PAL-2649 (die only) |
| Paladin Stripper | PAL-1248 | PAL-1248 | PAL-1248 | PAL-1248 | PAL-1248 |
| Canare Stripper | TS100U | TS100U | TS100U | TS100U | TS100U |

| Amphenol HD-BNC | Mini-RG59 Coax (1855 & 4855) | | | | |
|-----------------------|------------------------------|-------------------|--------------------|--------------------|-----------------------|
| Model | AMPH-034-1037 | 034-1026 | AMPH-034102612G | AMPH-034-110712G | AMPH-034-111812G |
| BNC Type | 3-Piece 3G HD-BNC | 3-Piece 3G HD-BNC | 3-Piece 12G HD-BNC | 3-Piece 12G HD-BNC | 2-Pc. 12G Right Angle |
| Contact Type | Beryllium Copper | Phosphor Bronze | Phosphor Bronze | | |
| Belden | 1855A / 1855P | 1855A / 1855P | 1855A / 1855P | 4855R / 4855P | 4855R / 4855P |
| Coax | | | | 1855A / 1855P | 1855A / 1855P |
| Amphenol Crimp Tool | AMPH-47-10120 | AMPH-47-10120 | AMPH-47-10120 | AMPH-47-10120 | AMPH-47-10120 |
| Paladin Crimper w/Die | PAL-1366 | PAL-1366 | PAL-1366 | PAL-1366 | PAL-1366 |
| Paladin Stripper | PAL-1258 | PAL-1247 | PAL-1247 | PAL-1258 | PAL-1258 |
| Canare Stripper | TS100U | TS100U | TS100U | TS100U | TS100U |

| Amphenol HD-BNC | RG59 (1505A & 4505R) | | |
|-----------------------|----------------------|--------------------|--------------------|
| Model | 034-1025 | AMPH-034102512G | AMPH-034-112012G |
| BNC Type | 3-Piece 3G HD-BNC | 3-Piece 12G HD-BNC | 3-Piece 12G HD-BNC |
| Contact Type | Phosphor Bronze | Phosphor Bronze | Phosphor Bronze |
| Belden | | | 4505R |
| Coax | 1505A | 1505A | 1505A |
| Amphenol Crimp Tool | AMPH-47-10110 | AMPH-47-10110 | AMPH-47-10110 |
| Paladin Crimper w/Die | PAL-1366 | PAL-1366 | PAL-1366 |
| Paladin Stripper | PAL-1247 | PAL-1247 | PAL-1247 |
| Canare Stripper | TS100U | TS100U | TS100U |

| Amphenol HD-BNC | RG6 Coax (4694 & 1694) | | | | 12G Series 7 Coax (4794R) |
|-----------------------|------------------------|--------------------|-------------------|--------------------|---------------------------|
| Model | 034-1017-300 | AMPH-034101712G | 034-1027 | AMPH-034-112112G | AMPH-034-110412G |
| BNC Type | 3-Piece 3G HD-BNC | 3-Piece 12G HD-BNC | 3-Piece 3G HD-BNC | 3-Piece 12G HD-BNC | 3-Piece 12G HD-BNC |
| Contact Type | Phosphor Bronze | Phosphor Bronze | Phosphor Bronze | Phosphor Bronze | Phosphor Bronze |
| Belden | | | | | 4794R |
| Coax | 1694A | 1694A | 1695A | 4694R | 1794A |
| Amphenol Crimp Tool | AMPH-CTL-17 | AMPH-CTL-17 | AMPH-47-10110 | AMPH-CTL-17 | AMPH-47-10110 |
| Paladin Crimper w/Die | PAL-8049 | PAL-8049 | PAL-1366 | PAL-8049 | PAL-2649 (die only) |
| Paladin Stripper | PAL-1248 | PAL-1248 | PAL-1248 | PAL-1248 | PAL-1248 |
| Canare Stripper | TS100U | TS100U | TS100U | TS100U | TS100U |