



## REMOTE CONTROL FOR PRC-970 MODEL PSR-970



### FEATURES

- ◆ Major Setup Controls
- ◆ Remote Control
- ◆ 1 RU
- ◆ No Power Required

The LINK PSR-970 Remote Control panel is designed to complement the LINK PRC-970 Processing Amplifier. The remote control panel receives its necessary power from the PRC-970 via a 15-pin sub-D connector. The familiar Proc Amp controls; Video Level, Chroma Level, White Clip, and Pedestal Level are available on the PSR-970 front panel. In addition; Black Clip, Sync Amplitude, and Color Burst Amplitude are recessed controls for operator set-up.

All adjustments are DC controlled, allowing the remote to be placed up to 250 feet away from its companion unit. A unique feature of the PSR-970 allows the user to select which controls will be active on the remote control panel by using the PRC-970's Manual/Presets switches.

The PSR-970 is housed in a sturdy 1RU chassis and backed by LINK's standard 10-year warranty.

# MODEL PSR-970 REMOTE CONTROL

## SPECIFICATIONS

### INPUTS:

Sub-D: ..... 15 pin D-Sub Connector

### FRONT PANEL CONTROLS:

Controls, Knobs: ..... Video Level, Chroma Level, White Clip & Pedestal Level  
Controls, Recessed: ..... Sync Level, Burst Level & Black Clip  
Switch: ..... Remote/By-pass

### ENVIRONMENTAL:

Temperature: ..... 0° to 50° ambient  
Humidity: ..... 0% to 90% non-condensing

### POWER:

Input: ..... Receives from PRC-970  
Power: ..... 3 Watts

### MECHANICAL:

Height: ..... 1 3/4"  
Width: ..... 19"  
Depth: ..... 4.5"  
Weight: ..... 2.5 lbs.



**LINK** ELECTRONICS, INC. ♦ 2137 Rust Avenue ♦ Cape Girardeau, MO 63703-7668  
Phone 573 334 4433 ♦ FAX 573 334 9255